

MENUMANAGER FOR CARES USERS

TABLE OF CONTENTS

| | |
|--|-----------|
| SETTING UP MENUMANAGER – FIRST TIME..... | 3 |
| SIGNING ON TO AN APPLICATION..... | 7 |
| OPENING ADDITIONAL SESSIONS/APPLICATIONS..... | 10 |
| LOGGING OFF..... | 12 |
| TROUBLESHOOTING | 16 |
| RE-STARTING A SESSION IF CARES IS CLOCKING..... | 16 |
| HOW TO CLOSE AN APPLICATION SELECTED IN ERROR | 16 |
| HELPFUL HINTS..... | 17 |
| SHORTCUT KEYS | 17 |
| CHANGING COLORS | 17 |
| CHANGE TEXT DISPLAY FOR EDSNET VIEWING | 18 |
| APPENDIX | 19 |
| ALTERNATIVES FOR THE JUMP AND MENU KEYS | 19 |
| SIGNING ON TO OTHER CARES ENVIRONMENTS | 20 |

Setting up MenuManager – First Time

The instructions below include the one-time, permanent steps to set up toggle keys to allow you to access more than one application (CARES and KIDS for example) on a single session. After this first setup, sign on to CARES following the instructions in the next section, “Signing on to CARES using MenuManager”.

1. Open a Mainframe session as you normally do.
2. At the Selection Screen, type **menumgr** (it is not case sensitive) then press **Enter**.

```

05/30/02  10:05:20      SELECTION SCREEN (USSMSG10)      VTAM: L0KKJ06A

          ATT          CBT1

      CICSBP          CICS DP          CICS DP24
      CICSFP3        CICSFP4          CICSHP          CICS P330

      EOSP           FH
      IMAGE          IMSBP          IMSFP

      MENUMGR
      WISMART

          REFRESH          TSO

THIS SYSTEM IS FOR AUTHORIZED USERS ONLY; SYSTEM ACCESS IS MONITORED.  BY USING
THIS SYSTEM YOU EXPRESSLY CONSENT TO THIS MONITORING.  EVIDENCE OF UNAUTHORIZED
ACCESS WILL BE PROVIDED TO THE APPROPRIATE LAW ENFORCEMENT AGENCIES.

ENTER SELECTION HERE:  menumgr

```

3. At the MenuMgr Sign On Screen; type your **CARES logon ID** - then **tab**; type your **password**; and press **Enter**.

```

05/30/02  10:06:49      MENUMGR SIGN ON SCREEN          VTAM: L0KKJ06A
                                                3278-2A

LOGON ID   ==> jx2373
PASSWORD   ==>

New Password ==>
Account      ==>

PF1=Help    PF3=Logoff

Please remember to logoff before terminating your session.
Thank you.

THIS SYSTEM IS FOR AUTHORIZED USERS ONLY, SYSTEM ACCESS IS MONITORED.  BY USING
THIS SYSTEM YOU EXPRESSLY CONSENT TO THIS MONITORING.  EVIDENCE OF UNAUTHORIZED
ACCESS WILL BE PROVIDED TO THE APPROPRIATE LAW ENFORCEMENT AGENCIES.

Copyright (C) 1984,1996 Computer Associates International, Inc.

```

4. At the Sign On Information screen press **Enter**.

```

SIGN ON INFORMATION FOR JX2373          Panelid - TEN0025

*****

ICH70001I JX2373    LAST ACCESS AT 14:18:36 ON WEDNESDAY, MAY 29, 2002

*****

TO PROCEED, HIT ENTER

COMMAND ==>

```

5. This takes you to the TPX MENU where each listing is a separate system. At the Command ==> line type **tpxadmin** and press **Enter**.

```

MENU FOR JX2373          Panelid - TEN0041

Jump=NONE          Menu=NONE          Return to Menu=ATTN      Terminal - L0KKJ06A
Cmdchar=/          Cmdkey=PA3          Return to Logo=PF3      Model    - 3278-2A
                                System   - TPXITS1

==> Session TPXADMIN has ended <==

Sessid  Stat    Sessid  Stat    Sessid  Stat    Sessid  Stat
-  ATT          -  CBT1      N/A      -  CICSBP          -  CICSBDP
-  CICSBDP24      -  CICSFP3          -  CICSFP4      N/A      -  CICSHP
-  CICSFP330      -  EOSP          -  EOSPM          -  FH
-  IMSBP          -  IMSD2          -  IMSFP          -  TSO
-  WISMART

Command ==> tpxadmin
PF1=Help  PF7/19=Up  PF8/20=Down  PF10/22=Left  PF11/23=Right  H =Cmd Help

```

6. On the TPX User Self-Maintenance Menu screen, select Option 1 (TPX User options) and press **Enter**.

```
TPX User Self-Maintenance Menu

Select Option ==> 1

      Userid: JX2373

1  TPX User Options
2  TPX Session Options

3  STX User Options
4  STX Session Options

Only options highlighted are authorized for you.

Help can be reached by pressing PF1 from the Command line or from any field.
If a short Help message appears, you can press PF1 again for detailed Help.

Values changed become effective at your next TPX or STX signon.

PF1=Help    PF3=End    PF4=Return    "CANCEL" cancel updates
```

7. The TPX Userid Maintenance Detail Panel screen is used to set “Jump” and “Menu” shortcut keys. Because every function key already has been assigned within CARES, the Page Up and Page Down keys have been chosen for the Jump and Menu shortcuts. If you access the EBT and EDS systems, you may wish to refer to the Appendix to learn about alternatives. Setting PA1 as the Jump key allows you to use the “Page Up” key on your keyboard to “scroll” or “jump” through any sessions or applications you have open. PA2 allows you to use the “Page Down” key to display the menu screen and select new sessions or applications. Examples are provided in the “Opening additional sessions/applications” section.

(Continues on next page)

To set the shortcuts; **Tab** to the Jump Key field and type **PA1**, then **Tab** down to the Menu Key field and type **PA2**.

| TPX Userid Maintenance Detail Panel | | | |
|---|--|------------------|-----------------|
| Command ==> | | Panelid | - TEN0165 |
| Userid: JX2373 | | Userid | - JX2373 |
| UserName: FOSBINDER, THERESA | | Termid | - LOKKJ06A |
| Location: | | Date | - 05/30/02 |
| Phone: | | Time | - 10:13:35 |
| Command character: - | | Profile defaults | System defaults |
| Command key: - | | | / |
| Jump key: pa1 | | | PA3 |
| Menu key: pa2 | | | NONE |
| Print key: - | | | NONE |
| Group name: TPXGROUP | | | NONE |
| Command class: - | | | D |
| Operator Cmd Cls: - | | | D |
| Update class: - | | | D |
| Stage 1 timeout: - | | 000020 | 20 |
| Stage 1 option: - | | L | L |
| Stage 2 timeout: - | | 000120 | 120 |
| Stage 2 option: - | | KI | KI |
| PF1=Help PF3=End PF4=Return PF8=Next Page "CANCEL" cancel | | | |

8. Press **PF3** to save the changes and return to the TPX User Self-Maintenance Menu; and then Press **PF3** again to go back to the TPX Menu Screen.

| MENU FOR JX2373 | | | | Panelid - TEN0041 | | | |
|---|------|------------|------|---------------------|------|---------------------|------|
| Jump=NONE | | Menu=NONE | | Return to Menu=ATTN | | Terminal - LOKKJ06A | |
| Cmdchar=/ | | Cmdkey=PA3 | | Return to Logo=PF3 | | Model - 3278-2A | |
| ==> Session TPXADMIN has ended <== | | | | | | System - TPXITS1 | |
| Sessid | Stat | Sessid | Stat | Sessid | Stat | Sessid | Stat |
| - ATT | | - CBT1 | N/A | - CICSBP | | - CICSDBP | |
| - CICSDBP24 | | - CICSFP3 | | - CICSFP4 | N/A | - CICSHP | |
| - CICSFP330 | | - EOSP | | - EOSPM | | - FH | |
| - IMSBP | | - IMSD2 | | - IMSFP | | - TSO | |
| - WISMART | | | | | | | |
| Command ==> | | | | | | | |
| PF1=Help PF7/19=Up PF8/20=Down PF10/22=Left PF11/23=Right H =Cmd Help | | | | | | | |

9. For the settings to take effect, log out of MenuManager. To log out, press **PF3**. Press **PF3** again.

Steps 5 - 8 are one-time changes. You do not need to perform these steps again unless you wish to change your Jump or Menu keys.

Signing on to an Application

This section demonstrates opening an application from the MenuManager Menu. The example is given for CARES Production, although any application is opened in this manner.

(Steps 1 – 4 are the same as in the previous section, refer to that section for screen prints if needed.)

1. Open a Mainframe session as you normally do.
2. At the Selection Screen, type **Menumgr** then press **Enter**.
3. At the Menumgr Sign On Screen; type your **logon ID** - then **tab**, type your **password**; and press **Enter**.
4. At the Sign On Information screen; press **Enter** (This takes you to the TPX MENU where each listing is a separate system).
5. Type the application name at the Command Line and press **Enter**. OR, position the cursor next to the application in the menu, type **S**, and press **Enter**.
6. Follow the normal procedure for opening the application (see special instructions for opening CARES environments other than Production at the end of the packet).

Step-by-step CARES Production example (starting from Step 5 above).

| | | | | | |
|------------------------------------|------|-------------------|------|---------------------|------|
| MENU FOR JX2373 | | Panelid - TEN0041 | | Terminal - LOKKJ06A | |
| Jump=NONE | | Menu=NONE | | Model - 3278-2A | |
| Cmdchar=/ | | Cmdkey=PA3 | | System - TPXITS1 | |
| ==> Session TPXADMIN has ended <== | | | | | |
| Sessid | Stat | Sessid | Stat | Sessid | Stat |
| - ATT | | - CBT1 | N/A | - CICSBP | |
| - CICS2P24 | | - CICSFP3 | | - CICSFP4 | N/A |
| - CICS3P30 | | - EOSP | | - EOSPM | |
| - IMSBP | | - IMSD2 | | - IMSFP | |
| - WISMART | | | | - TSO | |

OR, instead of typing the application name at the Command Line, type "S" next to the application in the Menu and press Enter.

Command ==> **imsfp**

PF1=Help PF7/19=Up PF8/20=Down PF10/22=Left PF11/23=Right H =Cmd Help

After 20 minutes of non-use, the MenuManager session times out.

```
LOCK-UP FOR JX2505                                PANELID - TEN0023

*****
*
*
*
*      CAUSE:  TERMINAL LOCKED
*
*      TO PROCEED, ENTER YOUR PASSWORD BELOW
*
*
*
*****

PASSWORD===>
```

Type your **password** (the one you entered on the MenuMgr Sign On Screen) at the prompt.

If you wish to close any or all applications from this point, type your password at the prompt, then follow the instructions in the “Logging Off” section.

After 2 hours of non-use, the entire MenuManager session will close. You must sign on again.

Opening Additional Sessions/Applications

You may open an additional CARES Production session or other applications such as KIDS, EOS, EDSNET or EBT*. *Note:* You will no longer have to type your Logon ID or password for every system you access/open. CARES, EOS, and KIDS share the same Logon ID and password and once entered on the MenuMgr Sign-On Screen, they are applied to all applications opened via MenuManager. When using MenuManager for systems with different Logon IDs and passwords (such as EDSNET or CSI's EBT system), you will receive a prompt screen to enter this information.

1. Press the **Page Down** key to access the TPX Menu. Open applications are highlighted.
2. On the Command line, type the application you wish to open (for a second CARES production session, use IMSFP2) and press **Enter**. OR, if the application is listed on the menu, position your cursor next to the application, type **S** and press **Enter**.
3. Continue with the login process for the application.
4. To "jump", or scroll, through applications you have open, use the **Page Up** key.

Follow the above steps to open and jump between as many applications as needed.

*If you use the Page Up or Page Down key to access the PF keys within EDS or CSI's system, please see "Alternatives for the Jump and Menu Keys" in the Appendix.

Step-by-step example – opening EOS

For this example, CARES production environment is already open. The example starts with Step 1 from the above instructions.

Press the **Page Down** key to display the TPX Menu screen.

| | | | | | |
|---------------------|------|--------------------|------|--------------------|-------------|
| MENU FOR JX2505 | | Panelid - TEN0041 | | Terminal - LOBXP2A | |
| Jump=PA1 | | Menu=PA2 | | Model - 3278-2A | |
| Cmdchar=/ | | Cmdkey=PA3 | | System - TPXITS2 | |
| Return to Menu=ATTN | | Return to Logo=PF3 | | | |
| Sessid | Stat | Sessid | Stat | Sessid | Stat |
| - ATT | | - CBT1 | N/A | - CICSBP | - CICS DP |
| - CICS DP24 | | - CICSFP3 | | - CICSHP | - CICS P330 |
| - EOSP | | - EOSPM | | - FH | - IMSBP |
| - IMSD2 | | - IMSFP | | - TSO | - WISMART |

Open applications are highlighted with a different font color.

Command ==>

PF1=Help PF7/19=Up PF8/20=Down PF10/22=Left PF11/23=Right H =Cmd Help

Open EOS by typing “EOSP” on the Command line OR positioning the cursor next to EOSP on the Menu. Press **Enter**.

```

MENU FOR JX2505                      Panelid - TEN0041
                                     Terminal - L0BXP2A
Jump=PA1      Menu=PA2      Return to Menu=ATTN  Model - 3278-2A
Cmdchar=/     Cmdkey=PA3    Return to Logo=PF3   System - TPXITS2

Sessid  Stat  Sessid  Stat  Sessid  Stat  Sessid  Stat
- ATT          - CBT1    N/A    - CICSBP      - CICS DP
- CICS DP24    - CICS FP3  - CICS HP      - CICS P330
- EOSP        - EOS PM   - FH           - IMS BP
- IMS D2      - IMS FP   - TSO          - WIS MART

Command ==> eosp
PF1=Help  PF7/19=Up  PF8/20=Down  PF10/22=Left  PF11/23=Right  H =Cmd Help

```

The first time EOS is accessed, the EOS Environment Selection Menu displays. After the first time, you may get the form selection screen – just continue to log in as you normally do.

```

PF 1/13 HELP-COMMAND ==>
-ENVIRONMENT SELECTION MENU-      (1 OF 1)      USER -> JX2505  LU -> VTPX2005
      SELECT ENVIRONMENT ==>
R      - PRODUCTION REPORTS
J      - PRODUCTION JCL

```

Access the reports following the normal process.

Pressing the Jump shortcut key will jump between CARES and EOS. Pressing the Menu shortcut key will display the TPX Menu.

Logging off

Each application or session must be closed by individually signing off. MenuManager offers some shortcuts to end applications, however these do not fully close the session and should not be used as this may cause problems.

To log off from MenuManager; first close each application individually. Use the **Page Up** key to scroll through open applications; closing each one. When all are closed, only the TPX Menu screen will display when Page Up is pressed. Open applications can also be viewed and selected from the TPX Menu – open applications are highlighted in a different font color. Select an application by typing “S” in the field next to the application. After closing the application, you will be returned to the TPX Menu. Finally, when all applications are closed, type **logoff** at the Command Line on the TPX Menu (OR, press PF3 twice).

Step-by-step example - log off from MenuManager when both CARES and EOS are open:

The TPX Menu highlights open applications with a different font color (get to the Menu by pressing the **Page Down** key).

MENU FOR JX2505
Panelid - TEN0041

Jump=PA1
Cmdchar=/

Menu=PA2
Cmdkey=PA3

Return to Menu=ATTN
Return to Logo=PF3

Terminal - LOBXPR2A
Model - 3278-2A
System - TPXITS1

| Sessid | Stat | Sessid | Stat | Sessid | Stat | Sessid | Stat |
|---------------|------|-----------------|------|-----------|------|-------------|------|
| - ATT | | - CBT1 | N/A | - CICSBP | | - CICS DP | |
| - CICS DP24 | | - CICS FP3 | | - CICS HP | | - CICS P330 | |
| - EOSF | | - EOS PM | | - FH | | - IMS BP | |
| - IMS D2 | | - IMS FP | | - TSO | | - WIS MART | |

Both EOSP and IMSFP are open. They are highlighted with a different color font on the TPX Menu.

Command ==>

PF1=Help PF7/19=Up PF8/20=Down PF10/22=Left PF11/23=Right H =Cmd Help

Sign off from CARES. Either select it from the Menu or press the Page Up key to scroll through open applications. Once in CARES, press **PF10**.

```
SMSF                                05/30/02 10:28
                                      JX2373 T FOSBINDER
```

```
***** CARES SIGN-OFF *****
```

```
*****
*      TO COMPLETE THE SIGN-OFF FROM CARES AND RETURN TO IMS :      *
*              1. DEPRESS ENTER                                     *
*****
*      TO COMPLETE THE SIGN-OFF FROM CARES AND EXIT OUT OF IMS :    *
*              1. DEPRESS ENTER                                     *
*              2. ENTER "/RCL"                                     *
*****
*              TO SIGN ONTO CARES AGAIN :                            *
*              1. DEPRESS ENTER                                     *
*              2. ENTER THE SIGN-ON TRANSACTION CODE               *
*****
```

Press **PF3**.

```
DFS2171I NO RESPONSE CONVERSATION ENDED
```

```
F2=IMS LOGIN   F3=EXIT   F4=IMS LOGIN   F5=HILL FARMS MENU
F12=EXIT
```

Press **PF3** again. The TPX menu will display.

| | | | | | | | |
|-----------------|------|------------|------|---------------------|------|--------------------|------|
| MENU FOR JX2505 | | | | Panelid - TEN0041 | | | |
| Jump=PA1 | | Menu=PA2 | | Return to Menu=ATTN | | Terminal - L0BXP2A | |
| Cmdchar=/ | | Cmdkey=PA3 | | Return to Logo=PF3 | | Model - 3278-2A | |
| | | | | | | System - TPXITS1 | |
| Sessid | Stat | Sessid | Stat | Sessid | Stat | Sessid | Stat |
| - ATT | | - CBT1 | N/A | - CICSBP | | - CICS DP | |
| - CICS DP24 | | - CICSFP3 | | - CICSHP | | - CICS P330 | |
| - EOSP | | - EOSPM | | - FH | | - IMSBP | |
| - IMSD2 | | - IMSFP | | - TSO | | - WISMART | |

Only EOSP remains open and highlighted in a different color font.

Command ==>

PF1=Help PF7/19=Up PF8/20=Down PF10/22=Left PF11/23=Right H =Cmd Help

Select EOSP or press the Page Up key. In this example, EOS is already at the Global Selection Screen:

```
PF 1/13 HELP-COMMAND ==>
-REPORT INDEX --> RINDX      SS9001 ITSEOSP.EOS.RINDX.UD001
-GLOBAL SELECTION-          USERS-> 5951
```

| | | | |
|--------------------|----------------|-------------------|------------------|
| FORM NAME | ==> C717 | APPL. (JOBNAME) | ==> PWC RPPB1 |
| REPORT NAME | ==> | DEFERRED ONLY | ==> <- ENTER Y |
| REPORT ROOTNAME | ==> | ALL REPORTS | ==> <- ENTER Y |
| NOTEPAD HEADER | ==> | | |
| USER/GROUP | ==> DWDCARE | PRINTED REPORTS | ==> <- ENTER Y/N |
| REPORT VERSION | ==> | DISPLAYED REPORTS | ==> <- ENTER Y/N |
| REPORT STATUS | ==> | | |
| FROM DATE AND TIME | ==> / | EXPIRATION DATE | ==> |
| TO DATE AND TIME | ==> / | ARCHIVAL DATE | ==> |
| DESTINATION | ==> | ROOM NUMBER | ==> |
| OUTPUT FORM | ==> CLASS ==> | LOCAL PRIORITY | ==> |
| WITH TOC ONLY | ==> <- ENTER Y | SELECTION ON TOC | ==> <- ENTER Y |

Press **PF3**.

```
PF 1/13 HELP-COMMAND ==>
-REPORT INDEX --> RINDX      SS9001 ITSEOSP.EOS.RINDX.UD001
-REPORT INDEX MANAGEMENT-

      SELECT FUNCTION ==>
                        1 - GLOBAL USER DIRECTORY
                        2 - GLOBAL EXTRACTION
                        3 - GLOBAL SELECTION

                        5 - REPORT INDEX INFORMATION
```

Continue to press **PF3** until you return to the TPX Menu.

Type **Logoff** on the Command line (or, press **PF3** twice).

```
MENU FOR JX2505          Panelid - TEN0041
                                Terminal - LOBXPR2A
Jump=PA1          Menu=PA2          Return to Menu=ATTN  Model - 3278-2A
Cmdchar=/          Cmdkey=PA3        Return to Logo=PF3   System - TPXITS1
      ==> Session EOSP has ended <==
Sessid  Stat  Sessid  Stat  Sessid  Stat  Sessid  Stat
- ATT          - CBT1      N/A      - CICSBP          - CICSDP
- CICSDP24      - CICSFP3          - CICSHP          - CICSP330
- EOSP          - EOSPM          - FH              - IMSBP
- IMSD2          - IMSFP          - TSO              - WISMART
```

All applications have been closed. Nothing is highlighted.

```
Command ==> logoff
PF1=Help  PF7/19=Up  PF8/20=Down  PF10/22=Left  PF11/23=Right  H =Cmd Help
```

Troubleshooting

Re-starting a session if CARES is clocking

If CARES is clocking, you must inactivate the session in order to be able to open a fresh session. There is a feature in MenuManager that will return you to the screen where you last were if the session is disconnected. However, if you are clocking, you won't want to return to the same place. The following procedures will inactivate the CARES session and allow you to access a new one.

1. Use the Attn key* to display the TPX Menu.
2. Type "i" next to the application that is clocking.
3. Sign back into the application.

*On many keyboards, the Attn key is Shift + Esc. To check your Attn key, from your Mainframe session, click on Options, Settings. From the categories at the left side of the display box, click once on Keyboard Maps. On the far right side, click once on Edit. A map of your keyboard will appear. Pressing and holding the Shift key will show you the keys that are available by holding the Shift key in combination with another key. While holding the Shift key, look at the upper leftmost key. If this key says "Attn", you can access the Attn key as described above. If not, and if you do not see the Attn key, use the instructions below if your session is clocking.

If you cannot locate your Attn key:

1. Close MenuManager by clicking once on the "Close Window" button (the "X" at the upper right of the screen).
2. At the pop up box asking if you wish to disconnect, click "Yes".
3. Log back into MenuManager.
4. At the TPX Menu screen, type "i" next to the application that was clocking and any other applications that were open at the time (they should be highlighted in a different font color).
5. Sign back into the application.

How to Close an Application Selected in Error

If you selected an application you do not have access to, check the display for logoff instructions (for example, the IMSBP screen instructs you to use PF3 to exit). If no instructions are displayed, type logoff. The screen will pause momentarily, then return you to the TPX Menu. The application will no longer be highlighted on the Menu.

Helpful Hints

Shortcut Keys

MenuManager has PF keys and shortcut commands that you may use. The following are suggested function and shortcut keys available when you are at the TPX Menu screen:


PF1 = Help. You can access Help from MenuManager screens. It will provide screen specific information as well as a menu selection for other topics.

L = Locks the MenuManager session (similar to locking Windows by pressing CTL+ALT+DEL). Type your password to re-open the session.

K = Shortcut to logoff from MenuManager. Use this from the Menu Screen instead of pressing PF3 twice. Note that all applications or sessions must be closed prior to using this command to prevent problems with dates or batch cycles.

Changing Colors

To change the color scheme of a session in MenuManager, click on Options and then Settings. The following box will appear:



Change Text Display for EDSNET viewing

Some users have reported that EDSNET is best viewed with the text display set to 43 x 80. Please read and follow the instructions carefully. Note that the impact of making the font change is that you will need to use the scroll bar on the TPX Menu screen and other screens may appear elongated, although functionality does not change.

Recommended: Make the change prior to signing in to MenuManager (from the green Selection Screen).

To change the text display of a session:

1. Click on Options and then Settings.
2. At the Left of the Settings box (under Categories), click once on Display.
3. Click once on the General tab. Click the down arrow button under "Text display options" and select 43 x 80.
4. At the Left of the Settings box (under Categories), click once on Font.
5. Change the size to 10 (leave the Font as Courier New).
6. Click on Apply. Click on OK.
7. Open MenuManager.

If you need to change the screen display back to the original setting, follow the instructions above and Select "Any Model" under "Text Display Options".

Appendix

Alternatives for the Jump and Menu Keys

The Page Up and Page Down keys were selected for the Jump and Menu Shortcuts as they are not used within CARES. However, some users of the EBT and EDS systems need them. The alternatives - PF keys - have all been assigned a function within CARES. However, you may determine that you don't use certain PF keys (some are subsystem specific) and you can assign them as the Jump or Menu key.

If you elect to use a PF key instead of the Page Up and/or Page Down keys, simply type the PF key on the TPX Userid Maintenance Detail Panel screen in Step 7 of the Setting Up MenuManager – First Time instructions.

Example:

| TPX Userid Maintenance Detail Panel | | | |
|---|----------|------------------------------------|-----------------|
| Command ==> | | Panelid | - TEN0165 |
| Userid: JX2373 | | Userid | - JX2373 |
| UserName: FOSBINDER, THERESA | | Termid | - L0KKJ06A |
| Location: | | Date | - 05/30/02 |
| Phone: | | Time | - 10:13:35 |
| Command character: - | | Profile defaults | System defaults |
| Command key: | - | PF23 has been set as the Jump Key. | |
| Jump key: | pf23 | | |
| Menu key: | pa2 | | |
| Print key: | - | | |
| Group name: | TPXGROUP | | |
| Command class: | - | | |
| Operator Cmd Cls: | - | | |
| Update class: | - | - | D |
| Stage 1 timeout: | - | 000020 | 20 |
| Stage 1 option: | - | L | L |
| Stage 2 timeout: | - | 000120 | 120 |
| Stage 2 option: | - | KI | KI |
| PF1=Help PF3=End PF4=Return PF8=Next Page "CANCEL" cancel | | | |

Note that selecting a PF key as a Jump or Menu key will override the function of that key within other applications. For example, if you are on a CARES screen that has PF23 as an option, pressing it will Jump to another application rather than perform its function within CARES.

The Jump and Menu screen can be reset by changing them on the TPX Userid Maintenance Detail Panel (Command = TPXADMIN). Close all applications first, and remember to log off MenuManager and log back in to set the change.

Signing on to Other CARES Environments

If you have a Training or UAT ID, you can open Training and UAT sessions within MenuManager.

1. Log into MenuManager using your Production ID (so you can still access CARES Production, EOS, KIDS etc. and to be able to use your Jump and Menu keys).
2. At the TPX Menu, type the application (IMSX, IMSC etc.) on the Command line. Note that 2 sessions are available for each: e.g. IMSX and IMSX2.
3. At the screen that says "Session Ready for Input", press **PF2** to bring up a login screen. This is required because the ID you use to access the UAT or Training environment is different than your production ID.
4. Enter the User ID and password for the environment you wish to open. Press **Enter**.
5. Continue the signon as appropriate for the environment.

If your MenuManager session times out, the password you enter is your Production password.